

SP

Type Name	Resistive Load	Type Name	Resistive Load	Type Name	Resistive Load	Circuit	Position () indicates momentary		
	AC 125V DC 250V 30V		AC 125V DC 250V 30V		AC 125V DC 250V 30V				
AWTA01	25A	AWTA11	20A	AWTA21	15A	SPST	ON 1-3	—	OFF
AWTD01	〃	AWTD11	〃	AWTD21	〃	SPDT	ON 2-3	—	ON 2-1
AWTE01	〃	AWTE11	〃	AWTE21	〃	〃	ON 2-3	OFF	ON 2-1
AWTF01	〃	AWTF11	〃	AWTF21	〃	〃	ON 2-3	—	〈ON〉 2-1
AWTG01	〃	AWTG11	〃	AWTG21	〃	〃	〈ON〉 2-3	OFF	〈ON〉 2-1
AWTH01	〃	AWTH11	〃	AWTH21	〃	〃	ON 2-3	OFF	〈ON〉 2-1

Terminal-number diagram


1

2

3

Marking Side

D-cut Side



2P

Type Name	Resistive Load	Type Name	Resistive Load	Type Name	Resistive Load	Circuit	Position () indicates momentary		
	AC 125V DC 250V 30V		AC 125V DC 250V 30V		AC 125V DC 250V 30V				
AWTK01	25A	AWTK11	20A	AWTK21	15A	DPST	ON 1-3 2-4	—	OFF
AWTN01	〃	AWTN11	〃	AWTN21	〃	DPDT	ON 2-3 1-4	—	ON 2-1 3-4
AWTP01	〃	AWTP11	〃	AWTP21	〃	〃	ON 2-3 1-4	OFF	ON 2-1 3-4
AWTR01	〃	AWTR11	〃	AWTR21	〃	〃	ON 2-3 1-4	—	〈ON〉 2-1 3-4
AWTS01	〃	AWTS11	〃	AWTS21	〃	〃	〈ON〉 2-3 1-4	OFF	〈ON〉 2-1 3-4
AWTT01	〃	AWTT11	〃	AWTT21	〃	〃	ON 2-3 1-4	OFF	〈ON〉 2-1 3-4

Terminal-number diagram

1

2

3


4

5


6

Marking Side

D-cut Side





Dimensions of Mounting Holes



✧Tighten the nut with the torque at maximum 15Kg · cm.

Terminals

2 Screw Terminals (15A only)		4 Quick Connect #187 (15A only)		5 Quick Connect #250 (20·25A only)	
SP	DP	SP	DP	SP	DP
					

✧Inquire us about those except above and customized products.

MEMO